

18W内置升压单声道D类音频功放

18W Boosted Mono Class D Amplifier

■ FEATURES

- Spread spectrum technology
- Output Power
18W ($V_{BAT}=3.7V$, $R_L=4\Omega$, THD+N=10%, $f_{IN} = 1kHz$)
16W ($V_{BAT}=3.7V$, $R_L=4\Omega$, THD+N=1%, $f_{IN} = 1kHz$)
8W ($V_{BAT}=3.3V$, $R_L=8\Omega$, THD+N=1%, $f_{IN} = 1kHz$)
- Power Supply V_{BAT} : 3.0V~12V
- High Efficiency Boost Converter
 - Adjustable switch peak current limit to avoid over-pulling on battery current
- Over Current Protection, Thermal Protection, over voltage protection function included
- Pb-Free Packages, ESOP16

- 扩频技术
- 输出功率
18W ($V_{BAT}=3.7V$, $R_L=4\Omega$, THD+N=10%, $f_{IN} = 1kHz$)
16W ($V_{BAT}=3.7V$, $R_L=4\Omega$, THD+N=1%, $f_{IN} = 1kHz$)
8W ($V_{BAT}=3.3V$, $R_L=8\Omega$, THD+N=1%, $f_{IN} = 1kHz$)
- V_{BAT} 供电范围: 3.0V至12V
- 高效升压功能
- 可调节最大限流值, 有效防止电池拉死
- 保护功能:过流/过热/过压保护功能
- 无铅封装, ESOP16

■ APPLICATIONS

· Bluetooth/Wi-Fi Speakers	· Portable Speakers	· 蓝牙/ Wi-Fi音箱	· 便携式音箱
· Smart speakers	· Smart Home	· 智能音箱	· 智能家居

■ DESCRIPTION

HT81297F, integrated with a boost converter, is a mono Class D audio amplifier that drives up to continuous 18W (10% THD+N, 1kHz) into 4ohm speaker from a Li-battery voltage. The output voltage of boost converter is forced into 9V or 12V and it provides to the class D amplifier. Configurable current limit is adopted to avoid accidental large peak current.


HT81297F integrates Spread Spectrum Control technology to achieve advanced EMI suppression. The Gain of HT81297F is 32dB.

As for protection function, over current protection function for speaker output terminals, over temperature protection function and over voltage protection for boost converter output are also prepared.

HT81297F是一款内置升压的单声道D类音频功率放大器,由锂电池供电时, THD+N=10%,能连续输出18W功率(4Ω负载)。HT81297F则内置固定升压, 提供一个固定9V或12V的升压给D类功放。HT81297F可配置升压限流值, 以防止过大的电流尖峰。

HT81297F具有先进的扩频功能来抑制EMI。HT81297F的增益为32dB。


此外, HT81297F集成了输出端过流保护、片内过温保护、升压过压保护等功能。

■ TYPICAL APPLICATION



■ ORDERING INFORMATION

Part Number	Package Type	Marking	Operating Temperature Range	Shipping Package / MOQ
HT81297FSPER	ESOP16 (SPE)	HT81297F YYYMAAB ¹	-40°C~85°C	Tape and Reel (R) / 2500pcs

Part Number




Production Tracking Code



¹ YYYMAAB is production tracking code

■ TERMINAL CONFIGURATION



HT81297F Top View

■ TERMINAL FUNCTION

Terminal No.	Name	I/O ¹	Description
1	SW	I	Boost and rectifying switch input. 升压整流开关输入端
2	COMP	O	Output of the internal error amplifier, the loop compensation network should be connected between this pin and the GND pin. 环路补偿脚, 接补偿电路到GND。
3	GVDD	O	Voltage regulator, connect 1uF to GND. 电压调节器, 接1uF到地。
4	AVCC	P	Analog power supply. 模拟供电
5	ILIM	I	Adjustable switch peak current limit. An external resistor should be connected between this pin and GND. 最大限流值设置端, 外部接电阻到地。
6	INP	I	Positive input (differential+) for audio amplifier. 功放输入正端
7	INN	I	Negative input (differential-) for audio amplifier. 功放输入负端
8, 9	NC	I	No connection. 内部无连接
10	CTRL	I	Mode Control Terminal. 模式控制脚
11	SN	I	Boost converter output voltage selection. 升压电压选择
12	BSP	BST	Connection point for the OUTP bootstrap capacitor, which is used to create a power supply for the high-side gate drive for OUTP. OUTP自举电容位
13	OUTP	O	Positive pin for differential speaker amplifier output. 输出正端
14	PVDD	P	Power Supply for internal power circuitry. 功率电源
15	OUTN	O	Negative pin for differential speaker amplifier. 输出负端
16	BSN	BST	Connection point for the OUTN bootstrap capacitor, which is used to create a power supply for the high-side gate drive for OUTN. OUTN自举电容位
EP	GND	G	Provides both electrical and thermal connection from the device to the board. A matching ground pad must be provided on the PCB and the device connected to it via solder. For proper electrical operation, this ground pad must be connected to the system ground. 既是地, 又是散热PAD

¹ I: Input; O: Output; G: Ground; P: Power; BST: BOOT Strap;

IMPORTANT NOTICE**注意**

Heroic Electronic Technology (Jiaxing) Co., Ltd (HT) reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any products or services. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

禾润电子科技（嘉兴）股份有限公司（以下简称HT）保留对产品、服务、文档的任何修改、更正、提高、改善和其他改变，或停止提供任何产品和服务的权利。客户在下单和生产前应确保所得到的信息是最新、最完整的。

HT assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using HT components.

HT对相关应用的说明和协助以及客户产品的板级设计不承担任何责任。

HT products are not authorized for use in safety-critical applications (such as life support devices or systems) where a failure of the HT product would reasonably be expected to affect the safety or effectiveness of that devices or systems.

HT的产品并未授权用于诸如生命维持设备等安全性极高的应用中。

The information included herein is believed to be accurate and reliable. However, HT assumes no responsibility for its use; nor for any infringement of patents or other rights of third parties which may result from its use.

本文中的相关信息是精确和可靠的，但HT并不对其负责，也不对任何可能的专利和第三方权利的侵害负责。

Following are URLs and contacts where you can obtain information or supports on any HT products and application solutions:

下面是可以联系到我公司的相关链接和联系方式：

**禾润电子科技（嘉兴）股份有限公司
Heroic Electronic Technology (Jiaxing) Co., Ltd.**

地址：浙江省嘉兴市南湖区亚太路906号科创CBD园区21号楼11层

Add: 11th floor, Building 21, No. 906, Yatai Road, Jiaxing, Zhejiang Province

Sales: 0573-82586608, sales@heroic.com.cn

Support: 0573-82586151, support@heroic.com.cn

Website: www.heroic.com.cn; wap.heroic.com.cn

Wechat MP: HEROIC_JX

请及时关注禾润官方微信公众号，随时获取最新产品信息和技术资料！

