

2×50W D类立体声音频功放

2x50W Class D Stereo Amplifier

■ FEATURES

- Output Power (BTL)
 - 2×40W (VDD=18V, RL=4Ω, THD+N=10%)
 - 2×50W (VDD=24V, RL=6Ω, THD+N=10%)
 - 2×40W (VDD=24V, RL=8Ω, THD+N=10%)
- Output Power (PBTL)
 - 80W (VDD=24V, RL=4Ω, THD+N=10%)
 - 100W (VDD=24V, RL=3Ω, THD+N=10%)
- Single Wide Voltage Supply: 4.5V-26V
- Efficiency > 90%
- Spread spectrum function
- MUTE function
- Differential / Single-ended Analog Input, BTL or PBTL Output
- Selectable Gain: 32dB or 26dB
- Integrated Self-protection Circuits Including Overvoltage, Undervoltage, Overtemperature, DC-detect, and Overcurrent with Error Reporting
- LF and HF Package of ETSSOP32

- 输出功率 (BTL)
 - 2×40W (VDD=18V, RL=4Ω, THD+N=10%)
 - 2×50W (VDD=24V, RL=6Ω, THD+N=10%)
 - 2×40W (VDD=24V, RL=8Ω, THD+N=10%)
- 输出功率 (PBTL模式)
 - 80W (VDD=24V, RL=4Ω, THD+N=10%)
 - 100W (VDD=24V, RL=3Ω, THD+N=10%)
- 单电源系统, 4.5V-26V宽电压输入范围
- 超过90%效率, 无需散热器
- 扩频功能
- MUTE功能
- 模拟差分/单端输入, 输出模式立体声/单声道可选
- 可选增益: 32dB/26dB
- 保护功能: 过压/过流/过热/欠压异常, 直流检测和短路保护
- 无铅无卤封装, ETSSOP32

■ APPLICATIONS

• Sound Bars	• Wireless Speakers	• 条形音箱	• 无线智能音箱
• Consumer Audio Applications	• TVs/Monitors	• 便携式音箱	• 消费类音频应用
		• 拉杆音箱	• LCD电视/监视器

■ DESCRIPTION


HT3386 is a stereo efficient, Class-D audio amplifier for driving speakers up to 50W/6 Ω in stereo BTL. It can also deliver 100W/3Ω power in stereo PBTL.

Spread spectrum function is available to achieve advanced EMI Suppression.

The built-in shutdown function can minimize the standby current of HT3386. The device also integrates MUTE function. HT3386 is fully protected against faults with Overvoltage, Undervoltage, Overtemperature, DC-detect, and Overcurrent protection. Faults can be reported to the processor to prevent devices from being damaged.

HT3386是一款高效D类音频功率放大器。在24V供电的立体声 (BTL)、THD+N=10%条件下,能够持续提供2*40W/6Ω功率输出;在单声道 (PBTL)、模式、THD+N=10%条件下,能够持续提供100W/3Ω功率输出。


HT3386具有先进的扩频功能来抑制EMI。此外,HT3386内置关断功能使待机电流最小化,同时内置了MUTE功能,还集成了过压保护、直流保护、短路保护、热保护和电源欠压异常保护等功能,可全面防止出现故障。

■ TYPICAL APPLICATION



■ ORDERING INFORMATION

Part Number	Package Type	Marking	Operating Temperature Range	Shipping Package / MOQ
HT3386MTER	ETSSOP32 (MTE)	HT3386 YYYMAAB ¹	-40°C~85°C	Tape and Reel (R) / 2000

Part Number




Production Tracking Code



¹ YYYMAAB is production tracking code

■ TERMINAL CONFIGURATION



HT3386 Top View

■ TERMINAL FUNCTION

Terminal No.	Name	I/O ¹	Description
1/3/6/13/14/15/16/22/28	NC	-	NC, Connect to Ground for better thermal performance
2	\SD/FAULT	I	SD/FAULT, multi-function pin. When pulled down, place the speaker amplifier in shutdown mode. General fault reporting including Over-Temp, Over-Current, DC Detect.
4	LINP	I	Positive input terminal for L channel
5	LINN	I	Negative input terminal for L channel
7	GVDD	O	Voltage regulator derived from AVDD supply, connect 1uF to GND
8	GAIN	I	Gain select pin. Low = 26dB gain; High or floating = 32dB
9,25	GND	G	Ground
10	RINN	I	Negative input terminal for R channel
11	RINP	I	Positive input terminal for R channel
12	MUTE	I	When pulled high, place the speaker amplifier in MUTE mode. When pulled low or be floating, place the speaker amplifier in normal operation.
17	AVCC	P	Analog power supply.
18,19	PVDDR	P	Power Supply for amplifier drivers of R channel
20	BSPR	BST	Connection point for the ROUTP bootstrap capacitor, which is used to create a power supply for the high-side gate drive for ROUTP
21	ROUTP	O	Positive pin for differential speaker amplifier output R
23	ROUTN	O	Negative pin for differential speaker amplifier output R
24	BSNR	BST	Connection point for the ROUTN bootstrap capacitor, which is used to create a power supply for the high-side gate drive for ROUTN

¹ I: Input; O: Output; G: Ground; P: Power; BST: BOOT Strap;

26	BSNL	BST	Connection point for the LOUTN bootstrap capacitor, which is used to create a power supply for the high-side gate drive for LOUTN
27	LOUTN	O	Negative pin for differential speaker amplifier output L
29	LOUTP	O	Positive pin for differential speaker amplifier output L
30	BSPL	BST	Connection point for the LOUTP bootstrap capacitor, which is used to create a power supply for the high-side gate drive for LOUTP
31,32	PVDDL	P	Power Supply for amplifier drivers of L channel
EP	NC	G	Provides thermal connection from the device to the board. A matching ground pad must be provided on the PCB and the device connected to it via solder. 散热PAD, 接地平面利于散热。

IMPORTANT NOTICE**注意**

Heroic Electronic Technology (Jiaxing) Co., Ltd (HT) reserves the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any products or services. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

禾润电子科技（嘉兴）股份有限公司（以下简称HT）保留对产品、服务、文档的任何修改、更正、提高、改善和其他改变，或停止提供任何产品和服务的权利。客户在下单和生产前应确保所得到的信息是最新、最完整的。

HT assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using HT components.

HT对相关应用的说明和协助以及客户产品的板级设计不承担任何责任。

HT products are not authorized for use in safety-critical applications (such as life support devices or systems) where a failure of the HT product would reasonably be expected to affect the safety or effectiveness of that devices or systems.

HT的产品并未授权用于诸如生命维持设备等安全性极高的应用中。

The information included herein is believed to be accurate and reliable. However, HT assumes no responsibility for its use; nor for any infringement of patents or other rights of third parties which may result from its use.

本文中的相关信息是精确和可靠的，但HT并不对其负责，也不对任何可能的专利和第三方权利的侵害负责。

Following are URLs and contacts where you can obtain information or supports on any HT products and application solutions:

下面是可以联系到我公司的相关链接和联系方式：

禾润电子科技（嘉兴）股份有限公司
Heroic Electronic Technology (Jiaxing) Co., Ltd.

地址：浙江省嘉兴市凌公塘路3339号JRC大厦A座三层

Add: A 3rd floor, JRC Building, No. 3339, LingGongTang Road, Jiaxing, Zhejiang Province

Sales: 0573-82585539, sales@heroic.com.cn

Support: 0573-82586151, support@heroic.com.cn

Fax: 0573-82585078

Website: www.heroic.com.cn; wap.heroic.com.cn

Wechat MP: HEROIC_JX

请及时关注禾润官方微信公众号，随时获取最新产品信息和技术资料！

